

















Vrednosti integrala  $\int_0^l f(x)g(x) dx$

								
	$lfg$	$\frac{1}{2}lfg$	$\frac{1}{2}lfg$	$\frac{1}{2}l(f_1 + f_2)g$	$\frac{2}{3}lfg$	$\frac{2}{3}lfg$	$\frac{1}{3}lfg$	$\frac{1}{3}lfg$
		$\frac{1}{3}lfg$	$\frac{1}{6}lfg$	$\frac{1}{6}l(2f_1 + f_2)g$	$\frac{5}{12}lfg$	$\frac{1}{3}lfg$	$\frac{1}{4}lfg$	$\frac{1}{12}lfg$
			$\frac{1}{3}lfg$	$\frac{1}{6}l(f_1 + 2f_2)g$	$\frac{1}{4}lfg$	$\frac{1}{3}lfg$	$\frac{1}{12}lfg$	$\frac{1}{4}lfg$
				$\frac{1}{6}l(f_1(2g_1 + g_2) + f_2(g_1 + 2g_2))$	$\frac{1}{12}lf(5g_1 + 3g_2)$	$\frac{1}{3}lf(g_1 + g_2)$	$\frac{1}{12}lf(3g_1 + g_2)$	$\frac{1}{12}lf(g_1 + 3g_2)$
					$\frac{8}{15}lfg$	$\frac{7}{15}lfg$	$\frac{3}{10}lfg$	$\frac{2}{15}lfg$
						$\frac{8}{15}lfg$	$\frac{1}{5}lfg$	$\frac{1}{5}lfg$
							$\frac{1}{5}lfg$	$\frac{1}{30}lfg$
								$\frac{1}{5}lfg$